

DS34RT5110 HDMI Cable Equalizer for 4k Resolution

Nasser Mohammadi

The DS34RT5110 can be used as a TMD5 equalizer, capable to support 3 data and 1 clock lines up to 3.4 Gbps per data line (or up to 340 MHz pixel clock). It is capable to support common display resolutions at 1080P/8-bit color at 1.485 Gbps per data line, or 1080P/12-bit at 2.25 Gbps, or 4k/8-bit resolution at 2.97 Gbps. The DS34RT5110 has on-chip 50Ω input terminations to 3.3V compatible to DC coupled TMD5 video source. Its output drivers are open-collector outputs compatible to DC coupled HDMI receiver downstream. The output drive amplitude is adjustable through an external resistor to GND.

Each one of the three data lines is equipped with a high gain equalizer, providing signal boost of up to about 27 dB at 3.4 Gbps. This high gain input stage enables the DS34RT5110 as a long reach user-settable HDMI cable equalizer, supporting 4k resolution. It is capable to extend the cable length, depending on the quality and wire gauge of the cable.

Figure 1 shows a simplified schematic diagram for using the DS34RT5110 as a HDMI repeater or a cable equalizer at the sink side.




Figure 1. DS34RT5110 as a Cable Equalizer

Table 1 illustrates the equalizer settings (EQ0-2) to set the level of equalization dependent on the insertion loss of the HDMI cable, which is determined by the length and wire gauge of the cable.

Table 1. Equalizer Boost Configuration

EQ Setting			EQ Boost
EQ2	EQ1	EQ0	Equalization in dB
			at 3.4 Gbps
0	0	0	0(default)
0	0	1	10
0	1	0	16
0	1	1	19
1	0	0	23
1	0	1	25
1	1	0	26
1	1	1	27

In a closed system where the video source is well defined, and does not have large amount of low frequency jitter (<4 MHz), using DS34RT5110 as a retimer can produce satisfactory result as a HDMI extender and retimer, allow longer distance and cascading operation. Connects pin 47 (BYPASS pin) to GND will set the DS34RT5110 as a HDMI retimer.

In open systems where the video source may have large amount of low frequency jitter (< 4 MHz), the DS34RT5110 as a retimer may not be able to handle this large amount of low frequency jitter, and may have difficulty to maintain the output data and clock lines as a synchronous bus, in which the data and clock lines maintain very similar jitter profiles in both the jitter amplitude and jitter frequency. Under this situation, setting pin 21 (MODE pin) to logic high will help to relief the jitter problem. In cases where the video source has excessive amount of low frequency jitter, the output of the DS34RT5110 may exceed the HDMI output eye template due to the low frequency jitter transferred to the output. In severe cases, there is a possibility of data integrity problem. In an open system where the video source is unknown and has high possibility it can be a video source with high level of low frequency jitter, it is recommended to use the DS34RT5110 as an equalizer as shown in [Figure 1](#).

For detail product information, please refer to the [DS34RT5110](#) datasheet at www.ti.com

IMPORTANT NOTICE

Texas Instruments Incorporated and its subsidiaries (TI) reserve the right to make corrections, enhancements, improvements and other changes to its semiconductor products and services per JESD46, latest issue, and to discontinue any product or service per JESD48, latest issue. Buyers should obtain the latest relevant information before placing orders and should verify that such information is current and complete. All semiconductor products (also referred to herein as "components") are sold subject to TI's terms and conditions of sale supplied at the time of order acknowledgment.

TI warrants performance of its components to the specifications applicable at the time of sale, in accordance with the warranty in TI's terms and conditions of sale of semiconductor products. Testing and other quality control techniques are used to the extent TI deems necessary to support this warranty. Except where mandated by applicable law, testing of all parameters of each component is not necessarily performed.

TI assumes no liability for applications assistance or the design of Buyers' products. Buyers are responsible for their products and applications using TI components. To minimize the risks associated with Buyers' products and applications, Buyers should provide adequate design and operating safeguards.

TI does not warrant or represent that any license, either express or implied, is granted under any patent right, copyright, mask work right, or other intellectual property right relating to any combination, machine, or process in which TI components or services are used. Information published by TI regarding third-party products or services does not constitute a license to use such products or services or a warranty or endorsement thereof. Use of such information may require a license from a third party under the patents or other intellectual property of the third party, or a license from TI under the patents or other intellectual property of TI.

Reproduction of significant portions of TI information in TI data books or data sheets is permissible only if reproduction is without alteration and is accompanied by all associated warranties, conditions, limitations, and notices. TI is not responsible or liable for such altered documentation. Information of third parties may be subject to additional restrictions.

Resale of TI components or services with statements different from or beyond the parameters stated by TI for that component or service voids all express and any implied warranties for the associated TI component or service and is an unfair and deceptive business practice. TI is not responsible or liable for any such statements.

Buyer acknowledges and agrees that it is solely responsible for compliance with all legal, regulatory and safety-related requirements concerning its products, and any use of TI components in its applications, notwithstanding any applications-related information or support that may be provided by TI. Buyer represents and agrees that it has all the necessary expertise to create and implement safeguards which anticipate dangerous consequences of failures, monitor failures and their consequences, lessen the likelihood of failures that might cause harm and take appropriate remedial actions. Buyer will fully indemnify TI and its representatives against any damages arising out of the use of any TI components in safety-critical applications.

In some cases, TI components may be promoted specifically to facilitate safety-related applications. With such components, TI's goal is to help enable customers to design and create their own end-product solutions that meet applicable functional safety standards and requirements. Nonetheless, such components are subject to these terms.

No TI components are authorized for use in FDA Class III (or similar life-critical medical equipment) unless authorized officers of the parties have executed a special agreement specifically governing such use.

Only those TI components which TI has specifically designated as military grade or "enhanced plastic" are designed and intended for use in military/aerospace applications or environments. Buyer acknowledges and agrees that any military or aerospace use of TI components which have **not** been so designated is solely at the Buyer's risk, and that Buyer is solely responsible for compliance with all legal and regulatory requirements in connection with such use.

TI has specifically designated certain components as meeting ISO/TS16949 requirements, mainly for automotive use. In any case of use of non-designated products, TI will not be responsible for any failure to meet ISO/TS16949.

Products

Audio	www.ti.com/audio
Amplifiers	amplifier.ti.com
Data Converters	dataconverter.ti.com
DLP® Products	www.dlp.com
DSP	dsp.ti.com
Clocks and Timers	www.ti.com/clocks
Interface	interface.ti.com
Logic	logic.ti.com
Power Mgmt	power.ti.com
Microcontrollers	microcontroller.ti.com
RFID	www.ti-rfid.com
OMAP Applications Processors	www.ti.com/omap
Wireless Connectivity	www.ti.com/wirelessconnectivity

Applications

Automotive and Transportation	www.ti.com/automotive
Communications and Telecom	www.ti.com/communications
Computers and Peripherals	www.ti.com/computers
Consumer Electronics	www.ti.com/consumer-apps
Energy and Lighting	www.ti.com/energy
Industrial	www.ti.com/industrial
Medical	www.ti.com/medical
Security	www.ti.com/security
Space, Avionics and Defense	www.ti.com/space-avionics-defense
Video and Imaging	www.ti.com/video

TI E2E Community

e2e.ti.com